

# mediaDROID - quick installation guide

be sure to read the complete FAQs section at <http://goo.gl/m7vlp>

## 1. Connections



Connect the **HDMI** port of the mediaDROID to your screen. Also connect a USB mouse (not supplied) to the mediaDROID's standard USB port. If you have a USB Hub, you can connect a standard keyboard, mouse and Ethernet dongle simultaneously.

The mediaDROID gets its power from a **micro USB port**. Connect the supplied micro USB cable to the mediaDROID and the other end of the USB cable to your screen's USB port (if it has one), or to the supplied 120V/240V power adapter.

## 2. Setup



When the mediaDROID is turned on, it will auto launch the SignageController and SignagePlayer. You will see a message indicating that the SignagePlayer is "**Checking Internet Connection...**".

With the mouse **RIGHT click** 2 times to go back to the [HOME SCREEN].

Next, connect the mediaDROID to the Internet. You can use the internal WIFI module or an external USB Ethernet dongle (sold separately). From the [HOME SCREEN] select **Apps > Settings > Wifi or Ethernet** tabs to configure the connection to a local WIFI / Ethernet switch.

You can use the Google browser App from the [HOME SCREEN] to check the connection.

## 3. Software updates



**IMPORTANT:** Be sure to register with Google Play so you can automatically receive remote updates for the SignagePlayer App. Click the [HOME SCREEN] Google Browser App & navigate to <http://android.digitalsignage.com>, once prompted, select to launch the Google Play store. Next click [UPDATE] for the SignagePlayer App & select [x] on the Auto updates check box.

## 4. Registration



Reboot the mediaDROID (unplug and re-connect the micro USB), this will auto launch the SignageController which in turn auto starts the SignagePlayer. Register the SignagePlayer with your mediaCLOUD *User name* and *Password*.

Launch the SignageStudio and begin remote managing your presentation. Enjoy!